

Busbar adapter, 9 mm

Part no.	BBA-XSM
Catalog No.	101484
Alternate Catalog No.	BBA-XSM
EL-Nummer (Norway)	2465059

Delivery program

Accessories		Busbar adapters
		Approved to UL 508 For fitting to flat Cu-busbars with 60 mm between busbar centres, suitable for 5 mm and 10 mm busbar thickness without electrical contact Side mounted module can be attached on both sides
Adapter width	mm	9
Adapter length	mm	200
Adapter width	mm	9
For use with		BBA...

Notes Can be grouped on the busbar adapter to extend mounting width.

Design verification as per IEC/EN 61439

Technical data for design verification		
Rated operational current for specified heat dissipation	I _n	A 0
Heat dissipation per pole, current-dependent	P _{vid}	W 0
Equipment heat dissipation, current-dependent	P _{vid}	W 0
Static heat dissipation, non-current-dependent	P _{vs}	W 0
Heat dissipation capacity	P _{diss}	W 0
Operating ambient temperature min.		°C -25
Operating ambient temperature max.		°C 55
IEC/EN 61439 design verification		
10.2 Strength of materials and parts		
10.2.2 Corrosion resistance		Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures		Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat		Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects		Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation		Meets the product standard's requirements.
10.2.5 Lifting		Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact		Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions		Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES		Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances		Meets the product standard's requirements.
10.5 Protection against electric shock		Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components		Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections		Is the panel builder's responsibility.
10.8 Connections for external conductors		Is the panel builder's responsibility.
10.9 Insulation properties		
10.9.2 Power-frequency electric strength		Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage		Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material		Is the panel builder's responsibility.
10.10 Temperature rise		Not applicable.
10.11 Short-circuit rating		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility		Is the panel builder's responsibility. The specifications for the switchgear must be observed.

Technical data ETIM 8.0

Low-voltage industrial components (EG000017) / Busbar adapter (EC001531)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Busbar trunking system (LV circuitry) / Busbar adapter (low-voltage switching technology) (ecl@ss10.0.1-27-37-03-04 [ACN951011])

Mounting rail armament			None
Type of electric connection			None
Rated current In	A	0	
Min. busbar thickness	mm	0	
Max. busbar thickness	mm	0	
Width of the adapter	mm	9	
Rail width	mm	0	
Busbar distance	mm	0	