## DATASHEET - PL6-D16/1

## Miniature circuit breaker (MCB), 16 A, 1p, characteristic: D

Part no.	PL6-D16/1
Catalog No.	286545



Similar to illustration

Delivery program			
Basic function			Miniature circuit-breakers
Number of poles			1 pole
Tripping characteristic			D
Application			Switchgear for residential and commercial applications
Rated current	In	A	16
Rated switching capacity according to IEC/EN 60898-1	I <sub>cn</sub>	kA	6
Product range	011		PL6
······································			
Technical data Electrical			
Rated switching capacity according to IEC/EN 60898-1	I <sub>cn</sub>	kA	6
Design varification as par IEC/EN 61/20			
Design verification as per IEC/EN 61439			
Technical data for design verification	1	٨	16
Rated operational current for specified heat dissipation	I <sub>n</sub>	A	16
Heat dissipation per pole, current-dependent	P <sub>vid</sub>	W	0
Equipment heat dissipation, current-dependent	P <sub>vid</sub>	W	2.2
Static heat dissipation, non-current-dependent	P <sub>vs</sub>	W	0
Heat dissipation capacity	P <sub>diss</sub>	W	0
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	75
			linear, per +1 °C, results in a 0.5% reduction of current carrying capacity
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting			Meets the product standard s requirements. Does not apply, since the entire switchgear needs to be evaluated.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.5 Lifting 10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated.
10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions			Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements.
10.2.5 Lifting         10.2.6 Mechanical impact         10.2.7 Inscriptions         10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated.
10.2.5 Lifting         10.2.6 Mechanical impact         10.2.7 Inscriptions         10.3 Degree of protection of ASSEMBLIES         10.4 Clearances and creepage distances			Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements.
10.2.5 Lifting         10.2.6 Mechanical impact         10.2.7 Inscriptions         10.3 Degree of protection of ASSEMBLIES         10.4 Clearances and creepage distances         10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated.
10.2.5 Lifting10.2.6 Mechanical impact10.2.7 Inscriptions10.3 Degree of protection of ASSEMBLIES10.4 Clearances and creepage distances10.5 Protection against electric shock10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated.
10.2.5 Lifting10.2.6 Mechanical impact10.2.7 Inscriptions10.3 Degree of protection of ASSEMBLIES10.4 Clearances and creepage distances10.5 Protection against electric shock10.6 Incorporation of switching devices and components10.7 Internal electrical circuits and connections			Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility.
10.2.5 Lifting10.2.6 Mechanical impact10.2.7 Inscriptions10.3 Degree of protection of ASSEMBLIES10.4 Clearances and creepage distances10.5 Protection against electric shock10.6 Incorporation of switching devices and components10.7 Internal electrical circuits and connections10.8 Connections for external conductors			Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility.
10.2.5 Lifting10.2.6 Mechanical impact10.2.7 Inscriptions10.3 Degree of protection of ASSEMBLIES10.4 Clearances and creepage distances10.5 Protection against electric shock10.6 Incorporation of switching devices and components10.7 Internal electrical circuits and connections10.8 Connections for external conductors10.9 Insulation properties			Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility. Is the panel builder's responsibility.
10.2.5 Lifting10.2.6 Mechanical impact10.2.7 Inscriptions10.3 Degree of protection of ASSEMBLIES10.4 Clearances and creepage distances10.5 Protection against electric shock10.6 Incorporation of switching devices and components10.7 Internal electrical circuits and connections10.8 Connections for external conductors10.9 Insulation properties10.9.2 Power-frequency electric strength			Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility. Is the panel builder's responsibility.

10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

## **Technical data ETIM 8.0**

Circuit breakers and fuses (EG000020) / Miniature circuit breaker (MCB) (EC000042)

Electric engineering, automation, process control engineering / Electrical installation, device / Miniature circuit breaker system (MCB) / Miniature circuit breaker (MCB) (ecl@ss10.0.1-27-14-19-01 [AAB905014])						
Built-in depth	m	ım	70.5			
Release characteristic			D			
Number of poles (total)			1			
Number of protected poles			1			
Rated current	A		16			
Rated voltage	V		230			
Rated insulation voltage Ui	V		440			
Rated impulse withstand voltage Uimp	k۱	V	4			
Rated short-circuit breaking capacity Icn according to EN 60898 at 230 V	k/	A	6			
Voltage type			AC			
Rated short-circuit breaking capacity Icn according to EN 60898 at 400 V	k/	A	6			
Rated short-circuit breaking capacity Icu according to IEC 60947-2 at 230 V	k/	A	0			
Rated short-circuit breaking capacity Icu according to IEC 60947-2 at 400 V	k/	A	0			
Frequency	Ha	z	50 - 60			
Current limiting class			3			
Flush-mounted installation			No			
Concurrently switching neutral conductor			No			
Over voltage category			3			
Pollution degree			2			
Additional equipment possible			Yes			
Width in number of modular spacings			1			
Degree of protection (IP)			IP20			
Ambient temperature during operating	°(	С	-25 - 75			
Connectable conductor cross section multi-wired	m	1m²	1 - 25			
Connectable conductor cross section solid-core	m	1m²	1 - 25			
Explosion-proof			No			