

Contact element, Cage Clamp, Front fixing, 1 N/O, 1 NC, 24 V 3 A, 220 V 230 V 240 V 4 A



Part no. M22-CK11
Catalog No. 107940
Alternate Catalog No. M22-CK11Q
EL-Nummer (Norway) 4355492

Delivery program

Product range	Accessories	
Basic function accessories	Contact elements	
Accessories	Auxiliary contact	
Accessories	Standard auxiliary contact, trip-indicating auxiliary switch	
Standard/Approval	UL/CSA, IEC	
Construction size	NZM1/2/3/4	
Description	When using emergency switching off actuators M22-PV... max. 2 contact elements = 4 NC / N/O contacts Cage Clamp is a registered trademark of Wago Kontakttechnik GmbH/Minden, Germany	
Connection technique	Cage Clamp	
Fixing	Front fixing	
Degree of Protection	IP20	
Connection to SmartWire-DT	no	
For use with	NZM1(-4), 2(-4), 3(-4), 4(-4) PN1(-4), 2(-4), 3(-4) N(S)1(-4), 2(-4), 3(-4), 4(-4)	
Contacts		
N/O = Normally open	1 N/O	
N/C = Normally closed	1 NC	
Notes	= safety function, by positive opening to IEC/EN 60947-5-1	
Actuator travel and actuation force as per DIN EN 60947-5-1, K.5.4.1		
Maximum travel	mm	4.8
Minimum force for positive opening	N	5.7
Connection type	20	
Description of HIA trip-indicating auxiliary contact	Double contact General trip indication '+', when tripped by shunt release, overload release, short-circuit release or by the residual-current release due to residual-current. Can be used with NZM1, 2, 3 circuit-breaker: a trip-indicating auxiliary contact can be clipped into the circuit-breaker. Can be used with NZM4 circuit-breaker: up to two standard auxiliary contacts can be clipped into the circuit-breaker. Any combinations of the auxiliary contact types are possible. Not in combination with switch-disconnector PN... Marking on switch: HIA Labeling in FI-Block: HIAFI. If the trip-indicating auxiliary switch in the fault current block is used, the NC contacts operate as a N/O contact and the NC contact operates as an N/O contact.	
Description standard auxiliary contact HIN	Used for indicating and interlocking tasks. Can be used with NZM1 circuit-breaker: a standard auxiliary contact can be clipped into the circuit-breaker. Can be used with NZM2 size circuit-breaker: a standard auxiliary contact can be clipped into the circuit-breaker. Can be used with NZM3, 4 circuit-breaker: up to three standard auxiliary contacts can be clipped into the circuit-breaker. Any combinations of the auxiliary contact types are possible. Marking on switch: HIN. On combination with remote operator NZM-XR... the right mounting location of standard auxiliary contact HIN can be fitted only with individual contacts.	
Connection technique	Cage Clamp	
Notes		
The following can be clipped into the switches:	<ul style="list-style-type: none"> • NZM1: a standard auxiliary contact 	

- NZM2: up to two M22-(C)K... standard auxiliary contacts
- NZM3: up to three M22-(C)K... standard auxiliary contacts
- NZM4: up to three M22-(C)K... standard auxiliary contacts

Any combinations of the auxiliary contact types are possible.

Marking on switch: HIN

In combination with remote operator NZM-XR... only single contacts can be fitted to some installation locations of the standard auxiliary contact.

NZM2: Only single contact can be fitted in left installation location of standard auxiliary contact.

NZM3: Only single contact can be fitted in installation locations of standard auxiliary contact.

NZM4: Only single contact can be fitted in right installation location of standard auxiliary contact.

Technical data

General

Standards			IEC 60947-5-1
Operating frequency	Operations/h		≤ 3600
Actuating force	n		≤ 10
Degree of Protection			IP20
Climatic proofing			Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30
Ambient temperature			
Open	°C		-25 - +70
Terminal capacities		mm ²	
Solid		mm ²	0.5 - 1.5
Stranded		mm ²	0.5 - 1.5
Flexible with ferrule		mm ²	0.5 - 1.5

Contacts

Rated impulse withstand voltage	U _{imp}	V AC	4000
Rated insulation voltage	U _i	V	250
Overtoltage category/pollution degree			III/3
Control circuit reliability			
at 24 V DC/5 mA	H _F	Fault probability	< 10 ⁻⁷ (i.e. 1 failure in 10 ⁷ operations)
at 5 V DC/1 mA	H _F	Fault probability	< 5 x 10 ⁻⁶ (i.e. 1 failure in 5 x 10 ⁶ operations)
Max. short-circuit protective device			
Fuseless		Type	PKZM0-10/FAZ-B6/1
Fuse	gG/gL	A	10

Switching capacity

Rated operational current	I _e	A	
AC-15			
115 V	I _e	A	4
220 V 230 V 240 V	I _e	A	4
DC-13			
24 V	I _e	A	3
42 V	I _e	A	1
60 V	I _e	A	0.8
110 V	I _e	A	0.5
220 V	I _e	A	0.3

Auxiliary contacts

Rated operational voltage	U _e	V	
Rated operational voltage	U _e	V AC	230
Rated operational voltage, max.	U _e	V DC	220
Conventional thermal current	I _{th} = I _e	CSA	4
Rated operational current	I _e	A	

								M22- (C)K10(01)		M22- CK11(02) (20)		XHIV
								bei AC = 50/60 Hz				
				Bemessungsbetriebsstrom								
		AC-1815	Ie	A	4	4	4					
		V										
		230	Ie	A	4	4	4					
		V										
		400	Ie	A	2	-	2					
		V										
		500	Ie	A	1	-	1					
		V										
		DC-124	Ie	A	3	3	3					
		V										
		42	Ie	A	1.7	1	1.5					
		V										
		60	Ie	A	1.2	0.8	0.8					
		V										
		110	Ie	A	0.6	0.5	0.5					
		V										
		220	Ie	A	0.3	0.2	0.2					
		V										
Rated conditional short-circuit current	I _q		kA	1								
Short-circuit protection												
max. fuse			A gG/gL	10								
Max. miniature circuit-breaker			A	FAZ-B6/B1								
Operating times												
								Early-make time of the HIV compared to the main contacts during with make and break switching.				
								(switch times with manual operation):				
								NZM1, PN1, N(S)1: ca. 20 ms				
								NZM2, PN2, N(S)2: ca. 20 ms				
								NZM3, PN3, N(S)3: ca. 20 ms				
								NZM4, N(S)4: approx. 90 ms, the HIV switch early Off switching not forward.				
Terminal capacities				mm ²								
Solid or flexible conductor, with ferrule				mm ²	1 x (0,5 - 1,5) 2 x (0,5 - 0,75)							
				AWG	1 x (20 - 18) 2 x (20 - 18)							
Other technical data (sheet catalogue)								Maximum equipment and position of the internal accessories				

Design verification as per IEC/EN 61439

Technical data for design verification													
Rated operational current for specified heat dissipation	I _n	A	4										
Heat dissipation per pole, current-dependent	P _{vid}	W	0.05										
Equipment heat dissipation, current-dependent	P _{vid}	W	0										
Static heat dissipation, non-current-dependent	P _{vs}	W	0										
Heat dissipation capacity	P _{diss}	W	0										
Operating ambient temperature min.		°C	-25										
Operating ambient temperature max.		°C	70										
IEC/EN 61439 design verification													
10.2 Strength of materials and parts													
10.2.2 Corrosion resistance									Meets the product standard's requirements.				
10.2.3.1 Verification of thermal stability of enclosures									Meets the product standard's requirements.				
10.2.3.2 Verification of resistance of insulating materials to normal heat									Meets the product standard's requirements.				
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects									Meets the product standard's requirements.				
10.2.4 Resistance to ultra-violet (UV) radiation									Meets the product standard's requirements.				
10.2.5 Lifting									Does not apply, since the entire switchgear needs to be evaluated.				
10.2.6 Mechanical impact									Does not apply, since the entire switchgear needs to be evaluated.				
10.2.7 Inscriptions									Meets the product standard's requirements.				
10.3 Degree of protection of ASSEMBLIES									Does not apply, since the entire switchgear needs to be evaluated.				
10.4 Clearances and creepage distances									Meets the product standard's requirements.				
10.5 Protection against electric shock									Does not apply, since the entire switchgear needs to be evaluated.				

10.6 Incorporation of switching devices and components		Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections		Is the panel builder's responsibility.
10.8 Connections for external conductors		Is the panel builder's responsibility.
10.9 Insulation properties		
10.9.2 Power-frequency electric strength		Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage		Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material		Is the panel builder's responsibility.
10.10 Temperature rise		The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function		The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 8.0

Low-voltage industrial components (EG000017) / Auxiliary contact block (EC000041)		
Electric engineering, automation, process control engineering / Low-voltage switch technology / Component for low-voltage switching technology / Auxiliary switch block (ecl@ss10.0.1-27-37-13-02 [AKN342013])		
Number of contacts as change-over contact		0
Number of contacts as normally open contact		1
Number of contacts as normally closed contact		1
Number of fault-signal switches		0
Rated operation current I_e at AC-15, 230 V	A	6
Type of electric connection		Spring clamp connection
Model		Top mounting and integrable
Mounting method		Front fastening
Lamp holder		None