

Auxiliary contact, 2early N/O, operates as an early-make contact



Powering Business Worldwide™

Part no. **NZM1-XHIV**
Catalog No. **259426**

EL-Nummer **4358868**
(Norway)

Technical data

Auxiliary contacts

Rated operational voltage	U _e	V						
Rated operational voltage	U _e	V AC	500					
Rated operational voltage, max.	U _e	V DC	220					
Conventional thermal current	I _{th} = I _e	CSA	4					
Rated operational current	I _e	A						
Different rated operational currents when used as auxiliary contact for NZM circuit-breaker				bei AC = 50/60 Hz			M22- K...	M22- CK...
				Bemessungsbetriebsstrom			XHIV	
				AC-1515	I _e	A	4	4
				V				
				230	I _e	A	4	4
				V				
				400	I _e	A	2	-
				V				2
				500	I _e	A	1	-
				V				1
				DC-124	I _e	A	3	3
				V				
				42	I _e	A	1.7	1
				V				1.5
				60	I _e	A	1.2	0.8
				V				0.8
				110	I _e	A	0.8	0.5
				V				0.5
				220	I _e	A	0.3	0.2
				V				0.2
Short-circuit protection								
max. fuse		A gG/gL	10					
Max. miniature circuit-breaker		A	FAZ-B6					
Operating times					Early-make time of the HIV compared to the main contacts during with make and break switching. (switch times with manual operation):			
					NZM1, PN1, N(S)1: ca. 20 ms			
					NZM2, PN2, N(S)2: ca. 20 ms			
					NZM3, PN3, N(S)3: ca. 20 ms			
					NZM4, N(S)4: approx. 90 ms, the HIV switch early Off switching not forward.			
Terminal capacities		mm ²						
Solid or flexible conductor, with ferrule		mm ²	1 x (0,75 - 2,5) 2 x (0,75 - 2,5)					
		AWG	1 x (18 - 14) 2 x (18 - 14)					
UL/CSA								
Rated operational current	I _e	A	2.5 A - 240 V AC 1 A - 250 V DC					
Heavy Pilot Duty			C300/R300					
Other technical data (sheet catalogue)				Maximum equipment and position of the internal accessories Time differences ON-OFF				

Design verification as per IEC/EN 61439

IEC/EN 61439 design verification		
10.2 Strength of materials and parts		
10.2.2 Corrosion resistance		Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures		Meets the product standard's requirements.

10.2.3.2 Verification of resistance of insulating materials to normal heat		Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects		Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation		Meets the product standard's requirements.
10.2.5 Lifting		Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact		Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions		Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES		Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances		Meets the product standard's requirements.
10.5 Protection against electric shock		Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components		Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections		Is the panel builder's responsibility.
10.8 Connections for external conductors		Is the panel builder's responsibility.
10.9 Insulation properties		
10.9.2 Power-frequency electric strength		Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage		Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material		Is the panel builder's responsibility.
10.10 Temperature rise		The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function		The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Auxiliary contact block (EC000041)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Component for low-voltage switching technology / Auxiliary switch block (ecl@ss10.0.1-27-37-13-02 [AKN342013])

Number of contacts as change-over contact		0
Number of contacts as normally open contact		2
Number of contacts as normally closed contact		0
Number of fault-signal switches		0
Rated operation current Ie at AC-15, 230 V	A	4
Type of electric connection		Screw connection
Model		Integrable
Mounting method		Other
Lamp holder		None