

Pushbutton, 250 V, 16A, 2 N/O, 1HP

Part no. Z-PU/SS
Catalog No. 276292



Similar to illustration

Technical data ETIM 8.0

| | | | |
|--|--|----|-------|
| Devices for distribution board-surface mounting (EG000062) / Push button for distribution board (EC001546) | | | |
| Electric engineering, automation, process control engineering / Electrical installation, device / Modular serial built-in device for electrical circuit distributors / Push button for distribution board (ec1@ss10.0.1-27-14-23-02 [AFZ814014]) | | | |
| Number of contacts as normally closed contact | | | 0 |
| Number of contacts as normally open contact | | | 2 |
| Number of contacts as change-over contact | | | 0 |
| Switching current | | A | 16 |
| Switching voltage | | V | 250 |
| Voltage type | | | AC |
| With signal lamp | | | No |
| Colour calotte | | | Other |
| Lamp type | | | LED |
| Lamp socket | | | Other |
| Max. lamp power | | W | 0 |
| Lamp voltage | | V | 0 - 0 |
| Colour button | | | Green |
| Width in number of modular spacings | | | 1 |
| Built-in depth | | mm | 60 |
| Degree of protection (IP) | | | IP40 |